Slim Type Ethernet I/O Modules





■ Introduction

The (P)ET-2261 provides 10 Form A electromechanical Relays Output channels. With 2 Ethernet ports, the (P)ET-2261 allows daisy chain connection which permits the flexibility in locating devices, eases installation and lowers infrastructure costs. It features 8 kV ESD protection, 4 kV EFT protection, 3 kV surge, and 3000 VDC I/O isolation to enhance noise protection capabilities in industrial environments.

■ System Specifications

Model	ET-2261	PET-2261
Software		
Built-in Web Server	Yes	
CPU Module		
CPU	32-bit ARM	
Watchdog Timer	Module, Communication (Programmable)	
Isolation		
2-way Isolation	Ethernet: 1500 VDC, I/O: 3000 VDC	I/O: 3000 VDC
EMS Protection		
EFT (IEC 61000-4-4)	±4 kV for Power Line	
ESD (IEC 61000-4-2)	±8 kV Contact for Each Terminal, ±16 kV Air for Random Point	
Surge (IEC 61000-4-5)	±3 kV for Power Line	
LED Indicators		
Status	Run, Ethernet, I/O	Run, Ethernet, I/O, PoE
Ethernet		
Ports	2 x RJ-45, 10/100 Base-Tx, Switch Ports	
LAN bypass	Yes	
PoE	-	Yes
Security	Password and IP Filter	
Protocol	Modbus TCP, Modbus UDP, MQTT, and SNMP V2c	
Power		
Reverse Polarity Protection	Yes	
Consumption	3.8 W (max.)	4.6 W (max.)
Powered from PoE	-	IEEE 802.3af, Class2
Powered from Terminal Block	+10 to +30 VDC	+10 to +48 VDC
Mechanical		
Casing	Plastic	
Dimensions (mm)	33 x 126 x 108 (W x L x H)	
Installation	DIN-Rail Mounting	
Environment		
Operating Temperature	-25 to +75°C	
Storage Temperature	-40 to +80°C	
Humidity	10 to 90% RH, Non-condensing	

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2023.04 1/2

■ I/O Specifications

Model	ET-2261	PET-2261		
Power Relay				
Channels	10			
Туре	Power Relay, Form A (SPST N.O.)			
Contact Rating	5 A @ 250 VAC/24 VDC (Resistive Load)			
Operate Time	10 ms	(max.)		
Release Time	5 ms (max.)			
Electrical Endurance	105	ops.		
Mechanical Endurance	2×10^7 ops.			
Power-on Value	Programmable			
Safe Value	Programmable			


Wire Connections


Power Relay	Relay Output	
ON State Readback as 1	AC/DC Load NOx COMx	
OFF State Readback as 0	AC/DC × NOx COMx	

Note:

When inductive loads are connected to the relays, a large counter electromotive force may occur when the relay actuates because of the energy stored in the load. These flyback voltages can severely damage the relay contacts and greatly shorten the relay life. Limit these flyback voltages at your inductive load by installing a flyback diode for DC loads or a metal oxide varistor for AC loads.


■ Pin Assignments





for DC loads Diode Load For AC loads Varistor Varistor

■ Dimensions (Units: mm)



Ordering Information

ET-2261 CR	Ethernet I/O Module with 2-port Ethernet Switch and 10-ch Power Relay (RoHS)
PET-2261 CR	PoE Ethernet I/O Module with 2-port Ethernet Switch and 10-ch Power Relay (RoHS)

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2023.04 2/2